

衛星系列產品

定向耦合器



| 1路 | | | | | | | |
|---------|-----------------------|----------------|--------|--------------------|-------------|-----|------|
| Model # | Frequency Range (MHz) | Insertion Loss | | Isolation Out-Port | Return Loss | | |
| | | In-Out | In-Tap | | In | Out | Port |
| SDC-108 | 10-40 | 2.8 | 8.0 | 22 | 12 | 15 | 14 |
| | 40-950 | 2.8 | 8.5 | 20 | 13 | 15 | 12 |
| | 950-1450 | 3.0 | 9.0 | 18 | 13 | 15 | 12 |
| | 1450-2150 | 4.5 | 10 | 18 | 10 | 15 | 10 |
| | 2150-2350 | 5.5 | 10 | 18 | 10 | 12 | 8 |
| SDC-112 | 10-40 | 1.7 | 12.5 | 20 | 15 | 16 | 12 |
| | 40-950 | 1.7 | 12.8 | 20 | 14 | 15 | 12 |
| | 950-1450 | 2.0 | 13.5 | 20 | 12 | 15 | 12 |
| | 1450-2150 | 3.0 | 14.5 | 18 | 10 | 14 | 10 |
| | 2150-2350 | 4.0 | 15 | 18 | 10 | 14 | 10 |
| SDC-116 | 10-40 | 1.7 | 16.5 | 25 | 15 | 16 | 20 |
| | 40-950 | 1.7 | 16.5 | 25 | 14 | 15 | 14 |
| | 950-1450 | 2.0 | 17 | 25 | 14 | 15 | 14 |
| | 1450-2150 | 3.0 | 18 | 20 | 10 | 15 | 12 |
| | 2150-2350 | 3.5 | 19 | 20 | 10 | 14 | 14 |
| SDC-120 | 10-40 | 1.5 | 20 | 28 | 16 | 18 | 16 |
| | 40-950 | 1.5 | 20.5 | 28 | 16 | 18 | 16 |
| | 950-1450 | 2.0 | 20 | 25 | 14 | 18 | 14 |
| | 1450-2150 | 3.0 | 21 | 22 | 10 | 15 | 10 |
| | 2150-2350 | 3.5 | 22 | 22 | 10 | 14 | 8 |
| SDC-124 | 10-40 | 1.0 | 24.5 | 40 | 18 | 20 | 16 |
| | 40-950 | 1.4 | 24.5 | 30 | 16 | 18 | 14 |
| | 950-1450 | 1.6 | 25 | 28 | 15 | 17 | 14 |
| | 1450-2150 | 2.5 | 26 | 26 | 12 | 14 | 14 |
| | 2150-2350 | 3.0 | 27 | 26 | 12 | 14 | 14 |
| SDC-128 | 10-40 | 1.2 | 28.5 | 40 | 18 | 20 | 18 |
| | 40-950 | 1.4 | 28.5 | 35 | 16 | 18 | 14 |
| | 950-1450 | 1.6 | 29.0 | 30 | 16 | 18 | 14 |
| | 1450-2150 | 2.5 | 29.5 | 28 | 12 | 15 | 14 |
| | 2150-2350 | 3.0 | 3.0 | 28 | 12 | 15 | 14 |